

Models:

SK8PM 1 x DI, 3 x UI, 2 x DO, 2 x UO – BACnet MS/TP

DS 40.03

February 2024

Overview

The Innotech SKIA BACnet Network Points Device provides 8 IO points for expansion and simple distributed points applications.

The device has no control logic capability but can be configured to suit the application and Input/Output combination required.

This highly flexible solution provides a mixture of digital and universal inputs and outputs making it suitable for a range of common, small point applications as part of a larger BACnet BMS network.

The SKIA SK8PM can be addressed and configured using Innotech Focus graphical programming interface software.

Features

- 8 Point Device with the following I/O types:
 - 1 x Digital Input (DI)
 - 3 x Universal Input (UI)
 - 2 x Digital Output (DO)
 - 2 x Universal Output (UO)
- 1 x RS-485 terminal
- Colour coded pluggable terminals for easy identification
- Communication LEDs
- Status LED
- Easily configured with Innotech Focus software
- DIN rail mountable

Applications

The SKIA BACnet Network Points Device has a small, flexible point count ideally suited to HVAC, Building and Energy Management, automation, and process control where it can act as an expansion or remote points device.

The SKIA provides a high point count density in a compact form factor and is suited to applications where available space may be restricted.

The configuration, network addressing, and device settings are modified using Innotech Focus engineering software. Focus' user friendly graphical programming interface provides power tools for the user to create a project-wide control strategy.

Typical applications include:

- Air conditioning and heating systems
- Lighting control
- Monitoring device
- Distributed I/O points

**Installation**

The device should be installed in an environment that does not exceed the maximum operating parameters of the device. It should be mounted in a clean and dry environment free of vibration, and properly ventilated.

The device should be mounted horizontally on a DIN rail in cabinets approved for switchgear or industrial control equipment.

Wiring should be implemented in accordance with Innotech connection diagrams and installation instructions as well as local bylaws. Refer to your local distributor for more information.

Connect the 24VAC or 24VDC supply to the correct terminals on the device. Maximum terminal cable entry is 1.5mm².

Model Specifications

Controller Name	SK8PM
Digital Inputs	1
Universal Inputs	3
Digital Outputs	2
Universal Outputs	2
RS-485 Ports	1
USB-Mini B (PC Link)	Yes
Innotech Smart Sensor Support	None
Max. Power per UI/O	0.8W
Max. IO System Power	3.6W

General Specifications

PROCESSOR	
CPU	ARM Cortex M7
Processor Speed	550MHz
POWER SUPPLY REQUIREMENTS	
Power Input	24VAC or 24VDC ±10%
Recommended Transformer Ratings	15VA min. (plus I/O load)
Power Consumption	5W (plus I/O load)
The operating voltage must meet the requirements of Safety Extra Low Voltage (SELV) to EN60730. The transformer used must be a class 2 safety transformer in compliance with EN60742 and be designed for 100% duty. It must also be sized and fused in compliance with local safety regulations.	
ENVIRONMENTAL	
Operating Temperature	-20° to 70°C non-condensing -4° to 158°F non-condensing
Storage Temperature	-40° to 80°C non-condensing -40° to 176°F non-condensing
INSTALLATION ORIENTATION	
Horizontally mounted DIN rail on a vertical surface. Allow a minimum 20mm (40mm recommended) gap between the end of the terminal plug and cable ducts.	
ENCLOSURE	
Housed in a rectangular case suitable for DIN rail mounting. Housing moulded from flame retardant plastics recognised by UL as UL94-VO.	
Colour	Dark Grey
DIMENSIONS AND WEIGHT	
W 124.6mm x H 111.8mm x D 40.0mm (4.90" x 4.40" x 1.57")	
SK8PM weight with all terminals fitted approx. 235g (0.52lbs)	
CLOCK	
Internal Real Time Clock	Not Battery Backed
BACnet Time Sync	Receive Only
APPROVALS AND LISTINGS	
EN 61326:2021 (IEC 61326:2020) Class B for CE & RCM Labelling	
Title 47 CFR, Part 15, Subpart B, Class B for FCC Marking	
UL Listed to UL916, File Numbers PAZX.E242628, PAZX7.E242628	
RoHS2	
Listed by BTL (B-ASC profile)	
Ingress Protection Rating – IP2X	
COMMUNICATIONS	
RS-485 Comms	Up to 115kbps (with EOL)

PROTOCOLS

RS-485	BACnet MS/TP
--------	--------------

DEFAULT ADDRESS

BACnet	2200
--------	------

CONFIGURING / MONITORING / COMMUNICATIONS

USB Device (Mini-B Type)	Innotech Net Comms Fixed #1 Address
Data Logging	Not Supported

LED INDICATION

Comms LEDs for RS-485	Red – TX, Green – RX
Heartbeat LED	Status OK Fault Request Power Fail
	Green Flash Red Flash Orange Flash Slow Orange Flash

 Request LED shown when upgrading, config transfer, initialising etc.

Inputs & Outputs

DIGITAL INPUT		DIGITAL OUTPUT	
Max Pulse Count Frequency	1kHz	Switch Mode	High Side Switching
Max Digital Input Response Rate	½ block cycle rate	Inrush and short circuit protection	On = 12VDC Off = Open
Max Digital Input Voltage	24V AC or DC	Switch Current	Self-Resetting Thermal Fuse
Digital Switching	On > 5.5VDC Off < 2VDC	Maximum Available Power	140mA
Digital Mode	Contact or Voltage		70mA

UNIVERSAL INPUTS		UNIVERSAL OUTPUTS	
Digital Input Configuration		Voltage Output Configuration	
Max Digital Input Response Rate	½ block cycle rate	Range	0VDC to 10VDC
Max Digital Input Voltage	24V AC or DC	Resolution	12bit @ 4096 steps
Digital Switching	On > 4VDC Off < 2VDC	Impedance	~100Ω
Digital Mode	Contact or Voltage	Maximum Current	20mA
Sensor Input Configuration		Accuracy	±1.5% of reading @ 20°C (68°F) & R _{load} > 10kΩ
Supports	Thermistor High, Thermistor Low	Drift	±150ppm/°C
Ranges	0 to 5VDC		
Resolution	16bit @ 65536 steps	Pulse Width Modulation (PWM) Output Configuration	
Accuracy	±1.5% of reading @ 20°C (68°F)	Frequency Range	12.5Hz
Drift	±150ppm/°C	High Side Switching	On = 12VDC Off = Open
Voltage Input Configuration		Duty Cycle Resolution	0.05%
Range	0 to 10VDC	Duty Cycle Range	0 to 100%
Resolution	16bit @ 65536 steps	Digital Output Configuration	
Max Input Voltage	24V AC or DC	High Side Switching	On = 12VDC Off = Open
Accuracy	±1.5% of reading @ 20°C (68°F)	Inrush and short circuit protection	Self-Resetting Thermal Fuse
Drift	±150ppm/°C	Switch Current	140mA
		Maximum Available Power	70mA

Warning: (Refer to Section 15.21 of 47 CFR)

In addition, the user's manual or instruction manual for an intentional or unintentional radiator shall caution the user that changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment (see example below).

Warning: Any changes or modifications not expressly approved by Innotech could void the user's authority to operate this equipment.

FCC CLASS B NOTICE

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference.

This device must accept any interference received, including interference that may cause undesired operation.

Note – This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential or commercial installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

SKIA SK8PM Controller Dimensions & Parts Identification

